

Sender Box

TS951

V1.0
Dec 2018

1. Function



- 1) One DVI video signal input;
- 2) One Audio signal input;
- 3) Supports reading back RCG;
- 4) Supports auto-sending RCG when replacing receiver
- 5) Supports auto-sending CON when replacing receiver
- 6) Sending card is set by USB; can be cascaded to drive a larger

Official website: www.linsn.com

Add: Floor 15&16, Jiajiahao Business Building, No. 10168, Shennan Blvd,
Nanshan District, Shenzhen

Tel: +86-0755-86183590/ 4008836968

screen, up to 4 cards cascaded;

- 7) Support adjusting brightness manually; three scales can be set: 16-grade, 32-grade and 64-grade;
- 8) Independent power supply;
- 9) Support 60Hz and 30Hz output mode;

2.Capability

60Hz mode (using two ports)	30Hz mode (using two ports)
2048 × 640	4032 × 512
1920 × 672	3840 × 544
1792 × 720	3584 × 576
1600 × 800	3392 × 608
1472 × 880	3200 × 640
1344 × 960	3072 × 672
1280 × 1024	2880 × 704
1024 × 1280 (require supporting by graphics card)	2560 × 800
832 × 1280 (require supporting by graphics card)	2368 × 864

Official website: www.linsn.com

Add: Floor 15&16, Jiajiahao Business Building, No. 10168, Shennan Blvd,
Nanshan District, Shenzhen

Tel: +86-0755-86183590/ 4008836968

640 × 1280 (require supporting by graphics card)	2048 × 1024
--	-------------

3. Specification

Specifications	
Model	TS951
Setting interface	USB
Input	DVI
Output	RJ45
Net weight (contains one sending card)	1.4KG
Length	280mm
Width	178mm
Height	50mm
Input voltage	100 ~ 240 V AC

END

Official website: www.linsn.com

Add: Floor 15&16, Jiajahao Business Building, No. 10168, Shennan Blvd,
Nanshan District, Shenzhen

Tel: +86-0755-86183590/ 4008836968